

FWV-DAT  
FWL-DAT  
FWM-DAT

| FW06       | MAX                |                | MED                |                | MIN                |                |
|------------|--------------------|----------------|--------------------|----------------|--------------------|----------------|
| AP<br>(Pa) | Power input<br>(W) | Current<br>(A) | Power input<br>(W) | Current<br>(A) | Power input<br>(W) | Current<br>(A) |
| 0          | 98                 | 0.430          | 68                 | 0.310          | 47                 | 0.220          |
| 10         | 96                 | 0.421          | 67                 | 0.305          | 45                 | 0.211          |
| 20         | 94                 | 0.412          | 64                 | 0.292          | 44                 | 0.206          |
| 30         | 91                 | 0.399          | 62                 | 0.283          | 43                 | 0.201          |
| 40         | 90                 | 0.395          | 61                 | 0.278          | 42                 | 0.197          |
| 50         | 89                 | 0.391          | 59                 | 0.269          |                    |                |
| 60         | 86                 | 0.377          | 56                 | 0.255          |                    |                |
| 70         | 82                 | 0.360          |                    |                |                    |                |