

Outdoor unit	Power supply					COMP		OFM		Symbols
Model name	Hz	Voltage	Voltage range	MCA	MFA	MSC	RLA	kW	FLA	
2MXM40M3V1B 2MXM40M4V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	12,21	16	-	5,1	0,040	0,17	MCA: Minimum Circuit Ampere [A]
	50	230					5,3			
	50	240					5,6			
2MXM50M2V1B9 2MXM50M3V1B9	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	14,93	16	-	5,9	0,042	0,18	MFA: Maximum Fuse Ampere [A]
	50	230					6,2			
	50	240					6,5			
2AMXM40M3V1B 2AMXM40M4V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	12,21	16	-	5,1	0,040	0,17	RLA: Rated load amps [A]
	50	230					5,3			
	50	240					5,6			
2AMXM50M3V1B 2AMXM50M4V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	14,93	16	-	5,9	0,042	0,18	OFM: Outdoor fan motor
	50	230					6,2			
	50	240					6,5			
2AMXF40A2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	12,21	16	-	5,1	0,040	0,17	MSC: Maximum starting current
	50	230					5,3			
	50	240					5,6			
2AMXF50A2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	14,93	16	-	5,9	0,042	0,18	FLA: Full Load Ampere [A]
	50	230					6,2			
	50	240					6,5			

Notes

- 1) The ·RLA· is based on the following conditions.
Outdoor temperature ·35·°C DB
Indoor temperature ·27·°C DB / ·19·°C WB
- 2) Select the wire size according to the MCA.
- 3) The maximum allowable voltage that is unbalanced between phases is ·2·%.
- 4) Use a circuit breaker instead of a fuse.