ARXM-A8
RXM-A8

Unit combination restriction		Power supply					COMP		OFM		IFM	
Outdoor unit	Indoor unit	Hz	Voltage	Voltage range	MCA	MFA	RHz	RLA	kW	FLA	kW	FLA
RXP50N5V1B8	FTXP50N5V1B9	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,81	13	62	7,0	0,052	0,63	0,050	0,60
		50	230					6,7				
		50	240					6,4				
RXM50A5V1B8	FTXM50A2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,6	0,052	0,63	0,040	0,36
		50	230					6,3				
		50	240					6,0				
RXM50A5V1B8	FTXM50A5V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,6	0,052	0,63	0,040	0,36
		50	230					6,3				
		50	240					6,0				
RXM50A5V1B8	FCAG50BVEB	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,48	13	57	6,7	0,052	0,63	0,048	0,30
		50	230					6,4				
		50	240					6,1				
RXM50A5V1B8	FBA50A2VEB9	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	12,69	13	58	6,8	0,052	0,63	0,089	1,40
		50	230					6,5				
		50	240					6,2				
RXM50A5V1B8	FHA50AVEB98	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,81	13	58	7,5	0,052	0,63	0,090	0,60
		50	230					7,2				
		50	240					6,9				
RXM50A5V1B8	FFA50A2VEB9	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,59	13	58	7,4	0,052	0,63	0,050	0,40
		50	230					7,1				
		50	240					6,8				
RXM50A5V1B8	FDXM50F3V1B9	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	12,14	13	57	7,7	0,052	0,63	0,060	0,90
		50	230					7,4				
		50	240					7,1				
RXM50A5V1B8	FNA50A2VEB9	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,70	13	57	7,1	0,052	0,63	0,060	0,50
		50	230					6,8				
		50	240					6,5				
RXM50A5V1B8	FVXM50B2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,30	13	58	6,4	0,052	0,63	0,037	0,14
		50	230					6,1				
		50	240					5,8				
ARXM50A5V1B8	ATXM50A2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,7	0,052	0,63	0,040	0,36
		50	230					6,4				
		50	240					6,1				
ARXM50A5V1B8	ATXM50A5V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,7	0,052	0,63	0,040	0,36
		50	230					6,4				
		50	240					6,1				
ARXM50A5V1B8	ADEA50A2VEB	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	12,69	13	58	7,3	0,052	0,63	0,089	1,40
		50	230					7,0				
		50	240					6,7				
RXM50A5V1B8	FTXM50B2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,6	0,052	0,63	0,040	0,36
		50	230					6,3				
		50	240					6,0				
RXM50A5V1B8	FTXM50B5V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,6	0,052	0,63	0,040	0,36
		50	230					6,3				
		50	240					6,0				
ARXM50A5V1B8	ATXM50B2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,7	0,052	0,63	0,040	0,36
		50	230					6,4				
		50	240					6,1				
ARXM50A5V1B8	ATXM50B5V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,54	13	62	6,7	0,052	0,63	0,040	0,36
		50	230					6,4				
		50	240					6,1				
RXM50A5V1B8	FVXM50C2V1B	50	220	MAX. 50Hz 264V MIN. 50Hz 198V	11,30	13	58	6,4	0,052	0,63	0,037	0,14
		50	230					6,1				
		50	240					5,8				

Symbols:

MCA: Minimum Circuit Amperes [A]
MFA: Maximum Fuse Amperes [A]
COMP: Compressor
RHz: Rated operating frequency [Hz]
RLA: Rated Load Amperes [A]
OFM: Outdoor fan motor
IFM: Indoor fan motor
kW: Fan motor rated output [kW]
FLA: Full Load Amperes [A]
MAX.: Maximum
MIN.: Minimum

Note:

1) The ·RLA· is based on the following conditions.
   Outdoor temperature ·35·°C DB
   Indoor temperature ·27·°C DB / ·19·°C WB
2) Select the wire size according to the MCA.
3) The maximum allowable voltage that is unbalanced between phases is ·2·%.
4) Use a circuit breaker instead of a fuse.