ARXP-P
RXP-P

Unit combination restrictions		Power supply					COMP		OFM		IFM	
Indoor unit	Outdoor unit	Hz	Voltage	Voltage range	MCA	MFA	RHz	RLA	kW	FLA	kW	FLA
FTXP20P5V1B	RXP20P5V1B	50	220	Maximum ·50·Hz ·264·V Minimum ·50·Hz ·198·V	7.99	16	40.0	2.5	0.024	0.17	0.021	0.30
		50	230					2.4				
		50	240					2.3				
FTXP25P5V1B	RXP25P5V1B	50	220	Maximum ·50·Hz ·264·V Minimum ·50·Hz ·198·V	7.99	16	48.0	2.7	0.024	0.17	0.023	0.33
		50	230					2.6				
		50	240					2.5				
FTXP35P5V1B	RXP35P5V1B	50	220	Maximum ·50·Hz ·264·V Minimum ·50·Hz ·198·V	9.20	16	76.0	4.2	0.021	0.16	0.032	0.39
		50	230					4.0				
		50	240					3.9				
ATXP20P5V1B	ARXP20P5V1B	50	220	Maximum ·50·Hz ·264·V Minimum ·50·Hz ·198·V	7.99	16	40.0	2.8	0.024	0.17	0.019	0.27
		50	230					2.7				
		50	240					2.6				
ATXP25P5V1B	ARXP25P5V1B	50	220	Maximum ·50·Hz ·264·V Minimum ·50·Hz ·198·V	7.99	16	49.0	2.9	0.024	0.17	0.020	0.28
		50	230					2.8				
		50	240					2.7				
ATXP35P5V1B	ARXP35P5V1B	50	220	Maximum ·50·Hz ·264·V Minimum ·50·Hz ·198·V	9.20	16	76.0	4.2	0.021	0.16	0.032	0.39
		50	230					4.0				
		50	240					3.9				

Notes

1) The ·RLA· is based on the following conditions.
   Outdoor temperature ·35·°C DB
   Indoor temperature ·27·°C DB / ·19·°C WB
2) Select the wire size according to the MCA.
3) The maximum allowable voltage that is unbalanced between phases is ·2·%.
4) Use a circuit breaker instead of a fuse.

Symbols

MCA: Minimum Circuit Ampere [A]
MFA: Maximum Fuse Ampere [A]
RLA: Rated load amps [A]
OFM: Outdoor fan motor
IFM: Indoor fan motor
RHz: Rated operating frequency [Hz]
FLA: Full Load Ampere [A]
kW: Fan motor rated output [kW]