

3MXS68G2V1B

Units						Power supply		Comp.		OFM	
Model	Hz	Hz	Volts	Min.	Max.	MCA	MFA	MSC	RLA		
3MXS68G2V1B	H/P	50	230	207	253	17.5	20	9.1	8.37	43	0.33

SYMBOLS

- MCA: Min. circuit Amps. (A)
MFA: Max. fuse Amps (A) (see note 6). (A)
MSC: Max. current during the starting compressor. (A)
RLA: Rated load Amps. (A)
DFM: Outdoor fan motor (A)
FLA: Full load Amps. (A)
w: Fan motor rated output (W.)

NOTES

- RLA is based on the following conditions.
Cooling:
Indoor temp. 27°CDB / 19.0°CWB
Outdoor temp. 35°CDB
- Voltage range.
Units are suitable for use on electrical systems where voltage supplied to unit terminal is not below or above listed range limits.
- Maximum allowable voltage variation between phases is 2%.
- MCA represents maximum input current. MFA represents capacity which may accept MCA.
- Select wire size based on the value of MCA.
- MFA is used to select the circuit breaker and the ground fault circuit interrupter (earth leakage circuit breaker).