

RXL35J

Representative unit combination		Power supply				Comp.		OFM		IFM	
Indoor unit	Outdoor unit	Hz-volts	Voltage range	MCA	MFA	RHz	RLA	W	FLA	W	FLA
FTXS35J	RXL35J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	9.75	10	65	3.9	23	0.23	23	0.15
							3.7				
							3.5				
FVXS35F	RXL35J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	9.75	10	65	4.8	23	0.23	48	0.05
							4.6				
							4.4				
FCQG35F	RXL35J	50 - 220 50 - 230 50 - 240	Max. 50Hz 253V Min. 50Hz 207V	9.75	10		7.1	23	0.23	48	0.30
							3.9				
							3.7				
FFQ35C	RXL35J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	9.75	10		4.8	23	0.23	50	0.40
							4.6				
							4.4				
FDXS35F	RXL35J	50 - 230	Max. 50Hz 253V Min. 50Hz 207V	12	16	90	5.5	35	0.22	34	0.30
FHQ35C	RXL35J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	9.75	10		4.3	23	0.23	60	0.60
							4.1				
							3.9				
FBQ35C8	RXL35J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	9.75	10	66	4.4	23	0.23	65	0.50
							4.2				
							4.0				

3D083676

SYMBOLS

MCA	: Min. Circuit Amps. (A)
MFA	: Max. Fuse Amps (A)
RLA	: Rated Load Amps. (A)
OFM	: Outdoor Fan Motor.
IFM	: Indoor Fan Motor.
FLA	: Full Load Amps. (A)
W	: Fan Motor Rated Output (W)
RHz	: Rated operating frequency (Hz)

NOTES

1. RLA is based on the following conditions:
Indoor temp.: 27°CDB/19°CWB
Outdoor temp.: 35°CDB
2. Maximum allowable voltage variation between phases is 2%.
3. Select wire size based on the larger value of MCA.
4. Instead of fuse, use circuit breaker.