

RXL50J

Representative unit combination		Power supply				Comp.		OFM		IFM	
Indoor unit	Outdoor unit	Hz-volts	Voltage range	MCA	MFA	RHz	RLA	W	FLA	W	FLA
FTXS50J	RXL50J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	19.75	20	66	6.3	53	0.27	23	0.15
							6.0				
							5.7				
FVXS50F	RXL50J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	19.75	20	69	6.7	53	0.27	48	0.10
							6.3				
							6.1				
FBQ50C8	RXL50J	50 - 230	Max. 50Hz 253V Min. 50Hz 207V	19.75	20		7	53	0.27	140	1.20
FFQ50C	RXL50J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	19.75	20	74	6.5	53	0.27	50	0.40
							6.2				
							5.9				
FCQG50F	RXL50J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	19.75	20		6.0	53	0.27	48	0.30
							5.7				
							3.4				
FHQ50C	RXL50J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	19.75	20		8.84	53	0.27	91	0.60
FDX550F	RXL50J	50 - 220 50 - 230 50 - 240	Max. 50Hz 264V Min. 50Hz 198V	19.75	20	74	6.8	53	0.27	36	0.40

3D080813A

SYMBOLS

MCA : Min. Circuit Amps. (A)
 MFA : Max. Fuse Amps (A)
 RLA : Rated Load Amps. (A)
 OFM : Outdoor Fan Motor.
 IFM : Indoor Fan Motor.
 FLA : Full Load Amps. (A)
 W : Fan Motor Rated Output (W)
 RHz : Rated operating frequency (Hz)

NOTES

1. RLA is based on the following conditions:
Indoor temp.: 27°CDB/19°CWB
Outdoor temp.: 35°CDB
2. Maximum allowable voltage variation between phases is 2%.
3. Select wire size based on the larger value of MCA.
4. Instead of fuse, use circuit breaker.