

RXS20-25K

Representative unit combination		Power supply				Comp.	OFM		IFM	
Indoor unit	Outdoor unit	Hz-volts	Voltage range	MCA	MFA	RLA	W	FLA	W	FLA
FTXS20K	RXS20K	50 - 220	Max. 50Hz 264V Min. 50Hz 198V	8.0	10	2.4	23	0.24	16	0.19
		50 - 230				2.2		0.23		0.18
		50 - 240				2.1		0.22		0.17
FTXS25K	RXS25K	50 - 220	Max. 50Hz 264V Min. 50Hz 198V	8.0	10	2.8	23	0.24	16	0.19
		50 - 230				2.7		0.23		0.18
		50 - 240				2.6		0.22		0.17

3D074810A

SYMBOLS

MCA : Min. Circuit Amps (A)
MFA : Max. Fuse Amps (A)
RLA : Rated Load Amps (A)
OFM : Outdoor fan motor
IFM : Indoor Fan Motor
FLA : Full Load Amps (A)
W : Fan Motor Rated Output (W)

- NOTES**
1. Maximum allowable voltage variation between phases is 2%.
 2. Select wire size based on the larger value of MCA.
 3. Instead of fuse, use circuit breaker.