

RXS35K

Representative unit combination		Power supply				Comp.		OFM		IFM	
Indoor unit	Outdoor unit	Hz-volts	Voltage range	MCA	MFA	RHz	RLA	W	FLA	W	FLA
FVXS35F	RXS35K	50 - 220 50 - 230 50 - 240	max. 50Hz 264V Min. 50Hz 198V	9.75	10	66	4.8	23	0.23	48	0.05
							4.6				
							4.4				
FLXS35B	RXS35K	50 - 220 50 - 230 50 - 240	max. 50Hz 264V Min. 50Hz 198V	9.75	10	66	4.5	23	0.23	34	0.38
							4.3				
							4.1				
FTXS35K	RXS35K	50 - 220 50 - 230 50 - 240	max. 50Hz 264V Min. 50Hz 198V	8.8	10	68	3.8	23	0.23	23	0.15
							3.6				
							3.4				

3D070943B

SYMBOLS

MCA	: Min. Circuit Amps (A)
MFA	: Max. Fuse Amps (A)
RLA	: Rated Load Amps (A)
OFM	: Outdoor fan motor
IFM	: Indoor Fan Motor
FLA	: Full Load Amps (A)
W	: Fan Motor Rated Output (W)
RHz	: Rated operating frequency (Hz)

NOTES

1. RLA is based on the following conditions:
Indoor temp.: 27°CDB/19°CWB
Outdoor temp.: 35°CDB
2. Maximum allowable voltage variation between phases is 2%.
3. Select wire size based on the larger value of MCA.
4. Instead of fuse, use circuit breaker.