

Representative unit combination		Power supply				Comp.		OFM		IFM	
Indoor unit	Outdoor unit	Hz-volts	Voltage range	MCA	MFA	RHz	RLA	W	FLA	W	FLA
FTXS50FV1B	RXS50F2V1B	50 - 220	Max. 50Hz 264V Min. 50Hz 198V	19.75	20.0	67	6.7	53	0.27	43	0.16
		50 - 230					6.4				
		50 - 240					6.1				
FTXS60FV1B	RXS60F2V1B	50 - 220	Max. 50Hz 264V Min. 50Hz 198V	19.75	20.0	84	8.7	53	0.32	43	0.16
		50 - 230					8.3				
		50 - 240					7.9				
FTXS71FV1B	RXS71FV1B	50 - 220	Max. 50Hz 264V Min. 50Hz 198V	19.75	20.0	57	10.3	66	0.40	43	0.19
		50 - 230					9.9				
		50 - 240					9.4				

3D056032A

SYMBOLS

MCA : Min. Circuit Amps (A)
 MFA : Max. Fuse Amps (A)
 RHz : Rated operating frequency (Hz)
 RLA : Rated Load Amps (A)
 OFM : Outdoor Fan Motor
 IFM : Indoor Fan Motor
 FLA : Full Load Amps (A)
 W : Rated motor output (W)

NOTES

1. RLA is based on the following conditions:
Indoor temp.: 27°CDB/19.0°CWB
Outdoor temp. : 35°CDB
2. Maximum allowable voltage unbalance between phases is 2%
3. Select wire size based on the larger value of MCA.
4. Instead of fuse, use circuit breaker.
5. For more details concerning conditional connections, see
<http://extranet.daikineurope.com>, select "E-Data Books". Finally, click on the document title of your choice.