

RXS50K

Representative unit combination		Power supply				COMP		OFM		IFM	
Indoor unit	Outdoor unit	Hz-volts	Voltage range	MCA	MFA	RHz	RLA	W	FLA	W	FLA
FVXS50F	RXS50K	50 - 220	Max. 50Hz 264V Min. 50Hz 198V	19.75	20	69	6.7	53	0.27	48	0.10
		50 - 230					6.3				
		50 - 240					6.1				
FTXS50K	RXS50K	50 - 220	Max. 50Hz 264V Min. 50Hz 198V	15.5	20	65	6.3	53	0.27	23	0.15
		50 - 230					6.0				
		50 - 240					5.7				

SYMBOLS	
MCA	: Min. Circuit Amps. (A)
MFA	: Max. Fuse Amps (A)
RLA	: Rated Load Amps. (A)
OFM	: Outdoor Fan Motor.
IFM	: Indoor Fan Motor.
FLA	: Full Load Amps. (A)
W	: Fan Motor Rated Output (W)
RHz	: Rated operating frequency (Hz)

NOTES	
1	RLA is based on the following conditions: Indoor temp.: 27°CDB/19°CWB Outdoor temp.: 35°CDB
2	Maximum allowable voltage variation between phases is 2%.
3	Select wire size based on the larger value of MCA.
4	Instead of fuse, use circuit breaker.

3D070939B