

RX20-35K

Unit combination restrictions		Power supply					COMP		OFM		IFM	
Indoor	Outdoor	1	2	3	MCA	MFA	RHz	RLA	kW	FLA	kW	FLA
FTX20J3	RX20K	50 50 50	220 230 240	MAX. 50Hz 264V MIN. 50Hz 198V	13,71	16	36	2,2	0,033	0,17	0,016	0,12
FTX25J3	RX25K	50 50 50	220 230 240	MAX. 50Hz 264V MIN. 50Hz 198V	13,71	16	48	3,2	0,033	0,17	0,016	0,12
FTX35J3	RX35K	50 50 50	220 230 240	MAX. 50Hz 264V MIN. 50Hz 198V	13,71	16	70	4,7	0,033	0,17	0,016	0,12

Notes

- 1
- The RLA is based on the following conditions.
Indoor temperature 27°C DB / 19°C WB
Outdoor temperature 35°C DB
- 2
- Select the wire size according to the MCA.
- 3
- The maximum allowable voltage that is unbalanced between phases is 2%.
- 4
- Use a circuit breaker instead of a fuse.

Symbols

- 1
- Hz
- 2
- Voltage
- 3
- Voltage range
- MCA
- Minimum Circuit Ampere (A)
- MFA
- Maximum Fuse Ampere (A)
- RLA
- Rated load amps [A]

- OFM
- Outdoor fan motor
- IFM
- Indoor fan motor
- FLA
- Full Load Ampere (A)
- kW
- Fan motor rated output [kW]
- RHz
- Rated operating frequency [Hz]

3D092100A