

RXS35L3

Unit combination restrictions		Power supply				COMP		OFM		IFM		
Indoor	Outdoor	A	B	C	MCA	MFA	RHz	RLA	kW	FLA	kW	FLA
FTXS35K3V1B	RXS35L3V1B	50	220	MAX. 50 Hz 264V	8,8	10	66	3,76	0,023	0,23	0,023	0,15
		50	230	MIN. 50Hz 198V				3,60				
		50	240					3,45				
FVXS35FV1B	RXS35L3V1B	50	220	MAX. 50 Hz 264V	9,75	10	76	4,81	0,023	0,23	0,048	0,05
		50	230	MIN. 50Hz 198V				4,60				
		50	240					4,41				
FLXS35BAVMB9	RXS35L3V1B	50	220	MAX. 50 Hz 264V	9,75	10	82	4,50	0,023	0,23	0,034	0,38
		50	230	MIN. 50Hz 198V				4,30				
		50	240					4,12				
FDXS35K2V1B	RXS35L3V1B	50	220	MAX. 50 Hz 264V	9,75	16	78	5,75	0,035	0,22	0,034	0,3
		50	230	MIN. 50Hz 198V				5,50				
		50	240					5,27				
FHQ35CAVEB	RXS35L3V1B	50	220	MAX. 50 Hz 264V	9,75	10	66	4,29	0,023	0,23	0,06	0,6
		50	230	MIN. 50Hz 198V				4,10				
		50	240					3,93				
FBQ35C8VEB	RXS35L3V1B	50	220	MAX. 50 Hz 264V	9,75	16	80	4,62	0,019	0,35	0,14	1,2
		50	230	MIN. 50Hz 198V				4,42				
		50	240					4,24				
FFQ35C2VEB	RXS35L3V1B	50	220	MAX. 50Hz 264V	9,75	10		4,80	0,023	0,23	0,050	0,4
		50	230	MIN. 50Hz 198V				4,60				
		50	240					4,40				
FCQG35FVEB	RXS35L3V1B	50	220	MAX. 50Hz 253V	9,75	10		7,10	0,023	0,23	0,048	0,3
		50	230	MIN. 50Hz 207V				3,90				
		50	240					3,70				

Notes

- The RLA is based on the following conditions.
Indoor temperature 27°C DB / 19°C WB
Outdoor temperature 35°C DB
- Select the wire size according to the MCA.
- The maximum allowable voltage that is unbalanced between phases is 2%.
- Use a circuit breaker instead of a fuse.

Symbols

A	Hz
B	Voltage
C	Voltage range
MCA	Minimum Circuit Ampere (A)
MFA	Maximum Fuse Ampere (A)
RLA	Rated load amps [A]

OFM	Outdoor fan motor
IFM	Indoor fan motor ^P
FLA	Full Load Ampere (A)
kW	Fan motor rated output [kW]
RHz	Rated operating frequency [Hz]