

FXMQ-MB

Units					Power supply		IFM		Input (W)	
Model	Type	Hz	Volts	Voltage range	MCA	MFA	kW	FLA	Cooling	Heating
FXMQ200MB	VE	50	220-240V	Max. 264V	10.3	16	1100	4.3	895	895
FXMQ250MB				Min. 198V	10.3	16	1100	5.6	1185	1185

SYMBOLS	
MCA	: Min. Circuit Amps. (A)
MFA	: Max. Fuse Amps. (See note 5)
kW	: Fan Motor Rated Output (kW)
FLA	: Full Load Amps. (A)
IFM	: Indoor Fan Motor.

NOTES	
1	Voltage range Units are suitable for use on electrical systems where the voltage supplied to the unit terminals is not below or above the listed range limits.
2	Maximum allowable voltage unbalance between phases is 2%.
3	MCA/MFA $MCA=1.25 \times FLA$ $MFA \leq 4 \times FLA$ (next lower standard fuse rating, min.15A)
4	Select wire size based on the MCA.
5	Instead of fuse, use circuit breaker.