

FXMQ-P7H

Units						Power supply	
Model	Type	Hz	Voltage range	Min.	Max.	MCA	MFA
FXMQ50P7	VE	50/60	220~240V/ 220V	-10%	+10%	1.4	16
FXMQ63P7						1.4	16
FXMQ80P7						1.7	16
FXMQ100P7						2.3	16
FXMQ125P7						2.9	16

NOTES

1. Voltage range
- Units are suitable for use on electrical systems where the voltage supplied to the unit terminals is not below or above listed range limits.
2. Maximum allowable voltage unbalance between phases is 2%.
3. Select wire size based on the MCA.
4. Instead of fuse, use circuit breaker.

SYMBOLS

MCA : Min. Circuit Amps. (A)  
MFA : Max. Fuse Amps. (See note 4)