

# FXZA-A

Model	Unit			Power supply		IFM	Power input [W]	
	Hz	Voltage	Voltage range	MCA	MFA	FLA	Cooling	Heating
FXZA15A2VEB	50/60	220-240/220	MAX. 264/MAX. 242 MIN. 198/MIN. 198	0,3	6	0,3	36	36
FXZA20A2VEB				0,3	6	0,3	36	36
FXZA25A2VEB				0,3	6	0,3	36	36
FXZA32A2VEB				0,4	6	0,4	38	38
FXZA40A2VEB				0,4	6	0,4	53	53
FXZA50A2VEB				0,6	6	0,5	86	86

## Notes

- 1) Voltage range  
The units are suitable for use with electrical systems in which the voltage supplied to the unit terminals is not below or above the listed range limits.
- 2) The maximum allowable voltage that is unbalanced between phases is -2%.
- 3)  $MCA = 1.1 \times FLA$
- 4) Select the wire size according to the MCA.
- 5) Use a circuit breaker instead of a fuse.

## Symbols

MCA: Minimum Circuit Ampere [A]  
MFA: Maximum Fuse Ampere [A]  
FLA: Full Load Ampere [A]  
IFM: Indoor fan motor