

VKM-GBM

Model	Power supply					IFM		Input (W)
	Hz	Volts	Voltage range	MCA	MFA	KW	FLA	
VKM50GBM	50	220 ~ 240V	Max. 264W Min. 198V	3.25	15	0.21 x 2	1.3 x 2	270
VKM80GBM				3.25	15	0.21 x 2	1.3 x 2	330
VKM100GBM				3.25	15	0.21 x 2	1.3 x 2	410

SYMBOLS

- MCA : Min. Circuit Amps (A)
 MFA : Max. Fuse Amps (See note 5)
 kW : Fan Motor Rated Output (kW)
 FLA : Full Load Amps (A)
 IFM : Indoor Fan Motor

NOTES

- Voltage range
Units are suitable for use on electrical systems where voltage supplied to unit terminals is not below or above listed range limits.
- Maximum allowable voltage unbalance between phases is 2%.
- MCA/MFA

$$MCA = 1.25 \times FLA_{(FM1)} + FLA_{(FM2)}$$

$$MFA \leq 4 \times FLA$$
 (Next lower standard fuse rating. Min. 15A)
- Select wire size based on the MCA.
- Instead of fuse, use circuit breaker.