

FWG-AT/AF

| Model | Speed | 1/1 Octave Sound Power Level (dB, reference 1pW) | | | | | | | Overall A (dBA) |
|------------|--------|--|-------|-------|------|------|------|------|-----------------|
| | | 125Hz | 250Hz | 500Hz | 1kHz | 2kHz | 4kHz | 8kHz | |
| FWG05AT/AF | High | 49 | 50 | 45 | 36 | 26 | 20 | 19 | 46 |
| | Medium | 46 | 44 | 39 | 28 | 16 | 15 | 18 | 40 |
| | Low | 38 | 40 | 32 | 22 | 14 | 15 | 20 | 34 |
| | Quiet | 33 | 38 | 24 | 15 | 10 | 14 | 18 | 30 |
| FWG08AT/AF | High | 59 | 58 | 56 | 50 | 42 | 42 | 30 | 67 |
| | Medium | 54 | 54 | 51 | 44 | 37 | 34 | 23 | 52 |
| | Low | 57 | 55 | 45 | 37 | 29 | 22 | 25 | 49 |
| | Quiet | 50 | 44 | 39 | 29 | 17 | 15 | 19 | 40 |
| FWG11AT/AF | High | 63 | 60 | 58 | 53 | 45 | 46 | 34 | 59 |
| | Medium | 60 | 55 | 54 | 48 | 40 | 40 | 27 | 55 |
| | Low | 58 | 50 | 49 | 41 | 34 | 29 | 20 | 49 |
| | Quiet | 53 | 45 | 42 | 33 | 22 | 16 | 19 | 43 |

Measured In Reverberation Chamber